CPU

* means validated by ECS at time of writing. Changes to component or CPU may produce a different outcome.
The result shown is for reference only and is subject to change w/o notification.

Socket	Family	Processor	Wattage	Frequency	Cache	Stepping	Since BIOS
LGA1151	Intel Core™ i7	8700	65W	3.20GHz	12MB	U0	81106
LGA1151	Intel Core™ i7	8700T	35W	2.40GHz	12MB	U0	81106
LGA1151	Intel Core™ i5	8400	65W	2.80GHz	9MB	U0	81106
LGA1151	Intel Core™ i5	8400T	35W	1.70GHz	9MB	U0	81106
LGA1151	Intel Core™ i5	8500	65W	3.00GHz	9MB	U0	81106
LGA1151	Intel Core™ i5	8500T	35W	2.10GHz	9MB	U0	81106
LGA1151	Intel Core™ i5	8600	65W	3.10GHz	9MB	U0	81106
LGA1151	Intel Core™ i5	8600T	35W	2.30GHz	9MB	U0	81106
LGA1151	Intel Core™ i3	8100	65W	3.60GHz	6MB	B0	81106
LGA1151	Intel Core™ i3	8100	65W	3.60GHz	6MB	U0	81106
LGA1151	Intel Core™ i3	8100T	35W	3.10GHz	6MB	B0	81106
LGA1151	Intel Core™ i3	8300	62W	3.70GHz	8MB	B0	81106
LGA1151	Intel Core™ i3	8300T	35W	3.20GHz	8MB	B0	81106
LGA1151	Intel Pentium Gold	G5400	58W	3.70GHz	4MB	U0	81106
LGA1151	Intel Pentium Gold	G5400	54W	3.70GHz	4MB	B0	81106
LGA1151	Intel Pentium Gold	G5400T	35W	3.10GHz	4MB	B0	81106
LGA1151	Intel Pentium Gold	G5400T	35W	3.10GHz	4MB	U0	81106
LGA1151	Intel Pentium Gold	G5500	54W	3.80GHz	4MB	B0	81106
LGA1151	Intel Pentium Gold	G5500T	35W	3.20GHz	4MB	B0	81106
LGA1151	Intel Pentium Gold	G5600	54W	3.90GHz	4MB	B0	81106
LGA1151	Intel Celeron	G4900	54W	3.10GHz	2MB	B0	81106
LGA1151	Intel Celeron	G4900T	35W	2.90GHz	2MB	B0	81106
LGA1151	Intel Celeron	G4920	54W	3.20GHz	2MB	B0	81106